

Ihs A7

## CLAIMS

Sub A8

1. Coherence controller (64) adapted for being connected to a plurality of  
2 processors (40, 40') equipped with a cache memory (42, 42') and with at least one local  
3 main memory (44) in order to define a local module (50) of basic multiprocessors (60),  
4 said coherence controller (64) including a cache filter directory (84) comprising a first  
5 filter directory SF designed to guarantee coherence between the local main memory (44)  
6 and the cache memories (42, 42') of the local module, characterized in that it also includes  
7 an external port (99) adapted for being connected to at least one external multiprocessor  
8 module (51, 52, 53) identical to or compatible with said local module (50), the cache filter  
9 directory (84) including a complementary filter directory ED for keeping track of the  
10 coordinates, particularly the addresses, of the lines or blocks of the local main memory  
11 (44) copied from the local module (50) into an external module (51, 52, 53) and  
12 guaranteeing coherence between the local main memory (44) and the cache memories (42,  
13 42') of the local module (50) and the external modules (51, 52, 53).

1 2. Coherence controller (64) according to claim 1, characterized in that it also  
2 includes an "n"-bit presence vector (86), where N is the number of basic multiprocessors  
3 in a module, an "N-1"-bit extension (88) of the presence vector, where N-1 is the total  
4 number of external modules (51, 52, 53) connected to the external port (99), and an  
5 Exclusive status bit (87).

1 3. Coherence controller (64) according to claim 2, characterized in that the  
2 external port (99) is connected directly or indirectly to the external modules (51, 52, 53)  
3 via an external two-point link (55).

1 4. Coherence controller (64) according to claim 2, characterized in that it  
2 includes "n" control units PU (80-83) of local ports (90-93) connected to the n basic  
3 multiprocessors (60-63) of the local module (50), a control unit XPU (89) of the external  
4 port (99) and a common control unit ILU of the filter directories SF/ED (84).

Sub A8  
1 5. Coherence controller (64) according to claim 4, characterized in that the  
2 control unit XPU (89) of the external port and the control units PU (80-83) of the local  
3 ports are compatible with one another and use similar, largely common protocols.

1 6. Multiprocessor module (50), characterized in that it includes a plurality of  
2 multiprocessors (60-63) equipped with at least one cache memory (42, 42') and at least  
3 one main memory (44) and connected to a coherence controller (64) according to any of  
4 claims 1 through 5.

1 7. Multiprocessor system with a multimodule architecture, characterized in that  
2 it includes at least two multiprocessor modules (50-53) according to claim 6, connected to  
3 one another directly or indirectly through the external ports (99) of the coherence  
4 controllers (64).

1 8. Multiprocessor system according to claim 7, characterized in that said  
2 external ports (99) are connected to one another through a switching device or router (54).

1 9. Multiprocessor system according to claim 8, characterized in that the  
2 switching device or router (54) includes means for managing and/or filtering the data  
3 and/or requests in transit.

1 10. Large-scale symmetric multiprocessor server with a multimodule architecture  
2 characterized in that it comprises "N" multiprocessor modules (50-53) that are identical or  
3 compatible with one another, each module comprising a plurality of "n" basic  
4 multiprocessors (60-63) equipped with at least one cache memory (42) and at least one  
5 local main memory (44) and connected to a local coherence controller (64) including a  
6 local cache filter directory SF designed to guarantee local coherence between the local  
7 main memory and the cache memories of the module, hereinafter called the local module,  
8 each local coherence controller (64) being connected by an external two-point link (55),  
9 possibly via a switching device or router (54), to at least one multiprocessor module (51,  
10 52, 53) outside said local module, the coherence controller (64) including a  
11 complementary cache filter directory ED for keeping track of the coordinates, particularly

